

FAP-440 Analog Detectors

www.boschsecurity.com



BOSCH

Invented for life



- ▶ Smoke threshold is adjustable and automatically compensated
- ▶ Rotary switch addressing
- ▶ Flexible work modes determined by the control panel
- ▶ Selectable base locking mechanism prevents malicious removal of the detector
- ▶ Multi-criteria or multi-sensor technology reduces false alarms

The FAP-440 Analog Detectors are open-area smoke detectors of which some models are enhanced with heat or heat and CO sensors. These detectors work with the FPA-1000 Analog Addressable Fire Panels. Use these detectors with the FAA-440 bases to provide general life safety and property protection.

Functions

Address Range

The FAP-440 Analog Detectors have a valid address range from 1 to 254 which is set by rotary switches on the back of each detector.

Indicator LED

The detector head has a multi-color LED to indicate status. To verify power to the detector and functioning communication of the analog addressable loop, the LED indicator flashes green when operating normally (polling). Through panel parameter setting, it is possible to turn on or off operation of the polling indicator. In the event of an alarm condition, the detector LED will always show a steady red light.

Modular Construction

These detectors are part of a two-piece modular design for detector assemblies. An FAP-440 Analog Detector attaches to an FAA-440 Family base. The base's security locking tab prevents any unauthorized detector removal from the base.

Advanced technology for false alarm reduction

Multi-sensor detector: The multi-sensor detector contains a photoelectric smoke sensor and a heat sensor. Either sensor can detect a fire and activate an alarm signal. The smoke threshold is adjustable (see Sensitivity Calibration and Compensation below) while the heat sensor's threshold is set at 135°F.

Multi-criteria detector: The multi-criteria detector also contains smoke and heat sensors that work independently of each other, but in conjunction with the CO sensor. In this model, an alarm signal will be activated by either one or both of the sensors only if the CO level is also exceeded.

**Notice****Carbon monoxide sensors:**

Detectors that contain carbon monoxide (CO) sensors must not be used as stand-alone CO detectors. The CO sensor is supplied to confirm the presence of CO as a by-product of combustion thereby reducing false alarms, but not to confirm the presence of CO as a hazardous gas.

Programming

Local programming is carried out at the panel keypad or by computer through a Web browser. Remote programming is carried out through a Web browser.

Sensitivity Calibration and Compensation

The sensitivity of the smoke sensor is programmable with 12 levels from which to choose. Throughout its normal life cycle, the smoke detector monitors itself against its factory calibrated level and periodically compensates itself to keep the sensitivity at its programmed level. When the detector is excessively contaminated, this condition will be annunciated at the control panel.

Certifications and approvals

Region	Certification	
USA	UL	UROX Smoke-automatic Fire Detectors (ANSI/UL 268)
	CSFM	see our website

Installation/configuration notes**Compatible Products**

The following products are compatible with the FAP-440 Series Analog Detectors:

Category	Product ID	Product Description
Fire Panels	FPA-1000 Series	Analog Addressable Fire Panels
Fire Panel Accessories	FPE-1000-SLC	Signaling Line Circuit Plug-in Module
Detector Bases	FAA-440-B4	4-inch Analog Standard Base
	FAA-440-B6	6-inch Analog Standard Base
	FAA-440-B4-ISO	4-inch Analog Isolator Base
	FAA-440-B6-ISO	6-inch Analog Isolator Base

Mounting Considerations

Detectors are typically mounted on the ceiling. However, if detectors are mounted on a wall, they must be at least 4 in. (10.2 cm), but no more than 12 in. (30.5 cm), below the ceiling. When other devices containing magnets or producing magnetic fields (for example, loudspeakers) are present in the

area, the base must be at least 1 ft (30 cm) from these devices to prevent unwanted activation of the test switch.

For UL Listing requirements, the spacing between smoke detectors should be no more than 30 ft (9.14 m).

Wiring Considerations

The control panel communicates to the detectors via the analog addressable loop (SLC), which allows the use of standard non-twisted, non-shielded wiring. The following wire gauges were tested and approved:

Wire Gauge	Maximum length
18 AWG (ISO 0.75 mm ²)	4000 ft (1200 m)
16 AWG (ISO 1.5 mm ²)	6225 ft (1900 m)
14 AWG (ISO 2.5 mm ²)	7200 ft (2200 m)
12 AWG (ISO 4 mm ²)	9850 ft (3000 m)

Remote Indicator

If a remote indicator is used in the circuit, it must be no more than 10 ft (3 m) from the base.

Parts included

Quant.	Component
1	FAP-440/-T/-TC Analog Detector
1	Dust cover

Technical specifications**Electrical**

Power provided via the SLC loop.

Current Draw

• Alarm:	5 mA
• Standby:	0.17 mA
• When polled:	22 mA ± 20%
Voltage (operating):	24 VDC to 41 VDC
Maximum allowable line resistance:	50 Ω maximum

Environmental

Protection category:	IP 42
Relative Humidity:	< 95% (non-condensing)
Installation temperature:	+32°F to +100°F (0°C to +38°C)

Storage Temperatures

• With CO sensor:	+14°F to +122°F (-10°C to +50°C)
• Without CO sensor:	-13°F to +176°F (-25°C to +80°C)

Mechanical

Dimensions	
• Detector:	4.4 in. x 2.0 in. (11.2 cm x 5.1 cm)
• Detector in 4-inch base:	5.0 in. x 2.5 in. (12.7 cm x 6.4 cm)
• Detector in 6-inch base:	7.0 in. x 2.5 in. (17.8 cm x 6.4 cm)
Housing Material:	CYCOLOY/ABS

Sensor

Airflow:	4000 ft/min (20 m/s) maximum
----------	------------------------------

Sensitivities

Smoke sensor:	1.25%/ft to 3.5%/ft (4.1%/m to 11.48%/m)
Heat sensor:	+135°F (+57°C) + RoR

Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

Ordering information**FAP-440 Analog Photoelectric Detector**

Order number **FAP-440**

FAP-440-T Analog Multisensor Detector Photo/Heat

Order number **FAP-440-T**

FAP-440-TC Analog Multicriteria Detector Photo/Heat/CO

Order number **FAP-440-TC**

Represented by:**Americas:**

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com