

# Remote Security Certificate Builder

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Extracts information from the Remote Programming Software (RPS) or A-Link Plus database and combines it into a certificate for the target Remote Security Control user
- ▶ Includes a start and an expiration date option to grant users access for a specific date range
- ▶ Shows compatible control panels only, and offers information on required RPS and A-Link Plus parameters
- ▶ Operates on the same computer as the remote programming software database, or a remote computer with database access
- ▶ Works with Microsoft Windows operating systems

Remote Security Certificate Builder (RSCB) is an account management utility for Microsoft Windows operating systems. It is designed to create certificates granting permissions to users to access specific control panels with Remote Security Control (RSC), which is an app for Android and Apple iOS devices.

## Functions

Remote Security Certificate Builder allows you to create certificates for users to connect to control panels through the Remote Security Control (RSC) app. Each user can connect to one control panel. Remote Security Certificate Builder extracts information from the remote programming software database and combines it into a certificate for the target RSC user. Once you create and send the certificates to the RSC mobile device, users can connect to and control compatible control panels for which you granted them access.

## Interface

The interface allows users to:

- Refresh programming changes made in remote programming software without closing the RSC

- Log in or log out without closing RSC

The interface provides users with:

- An easy-to-use wizard for selecting users and active certificate dates
- A filter for locating the desired compatible control panel

## Help

A Help file is accessed by pressing [F1] or through the Help menu. The Help file provides information about each field, button, and option in the software.

## Dealer information

The software includes the option to add your dealer information to the certificate, giving Remote Security Control users instant access to your contact information.

## Installation/configuration notes

### Installation and operation prerequisites

- The install process downloads and installs the required Microsoft .NET Framework 4 and Windows Installer 4.5.
- For Remote Security Certificate Builder installations on a computer that does not have remote programming software, the user must have access to the database.

### Compatible control panels

Remote Security Certificate Builder can create certificates for the following control panels:

- B9512G/B8512G, B9512G-E/B8512G-E (“E” variants require an Ethernet or cellular module.)
- B5512/B4512/B3512, B5512E/B4512E/B3512E (“E” variants require an Ethernet or cellular module.) With firmware v3.01 and higher require, these control panels require RSCB v1.6.0 or higher.
- D9412GV4/D7412GV4/D7212GV4 (Requires an Ethernet or cellular module.)
- Solution 2000/3000 (ICP-SOL2-P/ICP-SOL3-P) (Requires an Ethernet module.)

### Compatible devices for certificates

RSC and Remote Security Certificate Builder support both Android and iOS devices:

- Android devices with Android version 4.0.3 (Ice Cream Sandwich) and higher
- iPhone, iPod Touch, iPad with Apple iOS 6.0 and higher

### Compatible remote programming software

Remote Security Certificate Builder uses the remote programming software database to create certificates:

- Remote Programming Software v5.15.4 and higher
- A-Link Plus Remote programming Software v4.5 and higher

Note that your control panel and the latest Remote Security Control features might require the latest version of remote programming software.

## Technical specifications

### Minimum computer requirements

Processor	Pentium III, 800 MHz or faster
Operating system	<ul style="list-style-type: none"> <li>• Windows 8 (all editions)</li> <li>• Windows 7 (all editions)</li> <li>• Windows 2008 Server</li> <li>• Windows 2003 Server</li> <li>• Windows Vista (all editions)</li> </ul>

RAM	<ul style="list-style-type: none"> <li>• <b>Minimum:</b> 512 MB</li> <li>• <b>Recommended:</b> 1 GB or higher</li> </ul>
Communications	Ability to send email to the Remote Security Control device

### Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

## Ordering information

### Remote Security Certificate Builder

Available free of charge from the Bosch Security Systems, Inc., website, [us.boschsecurity.com](http://us.boschsecurity.com).

Order number **Remote Security Certificate Builder**

#### Represented by:

##### Americas:

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
[security.sales@us.bosch.com](mailto:security.sales@us.bosch.com)  
[www.boschsecurity.us](http://www.boschsecurity.us)

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
[emea.securitysystems@bosch.com](mailto:emea.securitysystems@bosch.com)  
[www.boschsecurity.com](http://www.boschsecurity.com)

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
[apr.securitysystems@bosch.com](mailto:apr.securitysystems@bosch.com)  
[www.boschsecurity.asia](http://www.boschsecurity.asia)

##### China:

Bosch (Shanghai) Security Systems Ltd.  
203 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
[www.boschsecurity.com.cn](http://www.boschsecurity.com.cn)

##### America Latina:

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
[latam.boschsecurity@bosch.com](mailto:latam.boschsecurity@bosch.com)  
[www.boschsecurity.com](http://www.boschsecurity.com)