



From	Product Management	Telephone	Nuremberg
ST-VS	ST-VS/MKP1	+49 911 93456 0	12-Jan-2015

Release Letter

Product:	<i>DIVAR IP 7000 Family</i>
Version:	<i>Maintenance Release DOM image v1.0.5</i>

This letter contains latest information about the above mentioned Bosch DIVAR IP 7000 Family.

1. General

DIVAR IP 7000 is an affordable, simple and reliable all-in-one recording, viewing and management solution for network surveillance systems of up to 128 channels (with 32 channels pre-licensed).

Running the full Bosch VMS (Video Management System) solution and powered by Bosch Video Recording Manager software, DIVAR IP 7000 is an intelligent IP storage device that eliminates the need for separate NVR (Network Video Recorder) server and storage hardware.

It combines advanced recording management and state-of-the-art iSCSI storage into a single cost-effective, plug and play IP recording appliance for IT-minded customers which are seeking for a state-of-the-art "second generation" NVR recording solution.

2. Restrictions; Known Issues

- Graphics Port: The DVI port must be used for configuration. Do not use the VGA port for configuration.
- Initial installation: During initial boot and installation the system must be connected to the network. Please note: All systems come with the same default IP address.
- Transcoder: Maximum transcoder source stream resolution is 1920x1080p30
- Mobile Video Service: the local MVS needs to be added to the system with the private IP address (not 127.0.0.1), if it shall serve as a fall-back transcoder for Operator Client access.
- BVC needs to be upgraded to version 1.6.2 or higher, if it shall serve as replay client for DIVAR IP 7000 appliances with BVMS 5.0.5
- VideoSDK needs to be upgraded to 5.81 MR1 or higher, if it shall serve as integration tool for DIVAR IP 3000 appliances with BVMS 5.0.5
- 3rd party device support restrictions are listed in the Bosch VMS release notes:
 - http://resource.boschsecurity.com/documents/Release_Notes_5.0.5_Release_Note_enUS_16781064459.pdf

3. New subcomponent software versions

- Bosch VMS 5.0.5.1010 (alternative installation option: BVMS 4.5.9.359)



From	Product Management	Telephone	Nuremberg
ST-VS	ST-VS/MKP1	+49 911 93456 0	12-Jan-2015

- Video Recording Manager 3.00.0074
- Video Streaming Gateway 5.91.0020
- USB-Transcoder Service 5.60.0078

4. New Features

System Setup

- Initial Setup procedure prompts a selection of two software installation options:
 - BVMS 5.0.5: recommended for most users
 - BVMS 4.5.9: recommended if system shall be integrated into existing BVMS 4.5.9 based infrastructure

Configuration Wizard (BVMS 5.0.5)

- Remote access: DNS information can be entered in the Basic step. The port rules for router configuration can be retrieved from the detailed report in the last wizard step.
- Network address of video devices to be added can be changed, if they are located in a different IP range.
- Recording profiles and retention time settings can be changed individually per device or for a selection of devices.

Management Server (BVMS 5.0.5)

- Additional data: option to record text data together with video stream

Video Streaming Gateway (BVMS 5.0.5)

- VSG supports alarm recording triggered by BVMS events

5. Applied Changes / Bug Fixes

BVMS 5.0.5

- Tested software/firmware versions, supported devices, bug fixes and change are listed in the Bosch VMS release notes:
http://resource.boschsecurity.com/documents/Release_Notes_5.0.5_Release_Note_enUS_16781_064459.pdf

Video Recording Manager

- Bug fixes and change are listed in the VRM release notes:
http://tutorials.ipp.boschsecurity.com/downloads/nue-mkp/VRM/3_00/Bosch_Releaseletter_VRM3_00_0073.pdf

Mobile Video Service

- Fixed: correct MVS entry shown in port mapping table for remote access
- Fixed: local MVS priority settings prevent system overload
- Changed: MVS web page can now be used: <https://<system-IP>/mvs>



From	Product Management	Telephone	Nuremberg
ST-VS	ST-VS/MKP1	+49 911 93456 0	12-Jan-2015

6. Installation Notes

- An upgrade from DOM Image v1.0.1 cannot be performed manually. DOM image v1.0.2 and later require a newer version of the system BIOS
- All models are based on Windows Server 2008 R2, 64-bit, Standard Edition

7. History

7.1 DIVAR IP 7000 DOM image version 1.0.4

Restrictions; Known Issues

- Graphics Port: The DVI port must be used for configuration. Do not use the VGA port for configuration.
- Initial installation: During initial boot and installation the system must be connected to the network. Please note: All systems come with the same default IP address.
- Transcoder: Maximum transcoder source stream resolution is 1920x1080p30
- ONVIF Support Restrictions
 - no support for event-based recording
 - Audio on some 3rd Party cameras not fully supported which may result in non-availability of audio streams
 - TCP not supported for ONVIF cameras but with UDP protocol only
 - Motion JPEG is not supported
 - VCA is always recorded for Bosch devices
 - VCA is not available for ONVIF cameras



From	Product Management	Telephone	Nuremberg
ST-VS	ST-VS/MKP1	+49 911 93456 0	12-Jan-2015

New subcomponent software versions

- BVMS 4.5.9.359
- VRM 3.00.0057

New Features

Image

- Added support for 3TB hard drives (DIVAR IP 7000 2U)
- Added support for partly populated hard drive layouts; 3 to 8 hard drives as part of a RAID 5 configuration (DIVAR IP 7000 2U)

Configuration Client and Configuration Wizard

- To avoid security issues, a global default password must be set for all devices and all authorization levels (service, live, user) that are not password protected. You can disable this enforced password protection for BVIP devices.
- VIP X16 XF E has been moved to Device Family 2 for support of 2nd stream for recording. Deviating from the behaviour of the other devices belonging to Device Family 2, VIP X16 XF E must use the same stream for all recordings. Although the user can configure stream 1 for continuous recording and stream 2 for alarm recording, the second setting will not take effect. After an Bosch VMS upgrade, perform the update of the device family manually.
To update the device family:
Right-click the device and click **Edit Encoder**.
Click **OK**.

Applied Changes / Bug Fixes

Image

- Fixed: DVD burner permission problem
- Fixed: 30days password expiration problem (last fix didn't apply in every case)
- Changed: Client software and documentation updated on the local network share

Operator Client

- Fixed: Click on find video by event results jumped to wrong playback time.
- Fixed: Live video images from NTSC cameras on DVR 670 were squeezed.
- Fixed: Sometimes OpClient could crash on loading favorites.
- Fixed: ONVIF domes could not be controlled.
- Fixed: Under rare circumstances OpClient could crash on logon of dual authorization group.
- Fixed: Video viewing via NAT/port mapping routes did not work on Windows XP.
- Fixed: Manual focus/iris in automatic mode.
- Tested software/firmware versions and supported devices (see BVMS 4.5.9 release notes for details → http://144.76.6.227/downloads/support-cctv/DIVAR_IP_3000/BVMS_VERSION_4_5_9_ReleaseNotes.pdf)



From	Product Management	Telephone	Nuremberg
ST-VS	ST-VS/MKP1	+49 911 93456 0	12-Jan-2015

Configuration Client

- Fixed: OPC Server Connection for BIS license option was not available.

Configuration Collector

- Fixed: Config Collector froze while zipping collected files.

VRM

- Fixed: Discovery is more stable
- Fixed: Reliability of disconnecting transcoders improved
- Fixed: Exporting Log-Files large than 100MB
- Changed: iSCSI-password is also set on USB-Transcoder

7.1 DIVAR IP 7000 DOM image version 1.0.2

Restrictions; Known Issues

- Graphics Port: The DVI port must be used for configuration. Do not use the VGA port for configuration.
- Initial installation: During initial boot and installation the system must be connected to the network. Please note: All systems come with the same default IP address.
- ONVIF Support Restrictions
 - no support for event-based recording
 - Audio on some 3rd Party cameras not fully supported which may result in non-availability of audio streams
 - TCP not supported for ONVIF cameras but with UDP protocol only
 - Motion JPEG is not supported
 - VCA is always recorded for Bosch devices
 - VCA is not available for ONVIF cameras

New subcomponent software versions

- BVMS 4.5.8.151
- VSG 5.60.0073
- Transcoder 5.60.0073
- .NET Framework 4.5

New Features

- Unlisted Bosch BVIP video devices can be added as generic devices (see BVMS 4.5.5 release notes for details).
- Server Lookup improvements (see BVMS 4.5.8 release notes for details).



From	Product Management	Telephone	Nuremberg
ST-VS	ST-VS/MKP1	+49 911 93456 0	12-Jan-2015

- Minor changes in the user and workstation settings (see BVMS 4.5.8 release notes for details).
- Client software and documentation can be downloaded from local network share.

Applied Changes / Bug Fixes

- Fixed: 30days password expiration problem
- Fixed: Windows activation problem
- Fixed: iSCSI LUN preparation problem
- Fixed: firewall rule exceptions
- Wizard prompts system reboot option when Network settings are changed
- Minor fixes in new subcomponent software versions (BVMS, VRM, VSG, Transcoder)
- Minor improvements in the initial installation procedure
- Tested software/firmware versions and supported devices (see BVMS 4.5.8 release notes for details → http://144.76.6.227/downloads/support-cctv/DIVAR_IP_3000/BVMS_VERSION_4_5_8_ReleaseNotes_v1.pdf).
- Bosch VMS default screen now shows text labels below the icons.
- The default network settings now match the default network settings of other Bosch video devices
 - IP Address: 192.168.0.200
 - Subnet mask: 255.255.255.0

Installation Notes

- An upgrade from DOM Image v1.0.1 cannot be performed manually. DOM image v1.0.2 requires a newer version of the system BIOS
- All models are based on Windows Server 2008 R2, 64-bit, Standard Edition

7.2 DIVAR IP 7000 DOM image version 1.0.1

Restrictions; Known Issues

- Graphics Port: The DVI port must be used for configuration. Do not use the VGA port for configuration.
- Password of limited operational Windows user expires after 30 days:
 - The password of limited user must be set manually to “never expires” on DIVAR IP 7000 by logging on to the DIVAR IP via remote desktop with user administrator user “BVRAdmin”. In the “Server Manager” the password can be changed to “Password never expires” (Configuration → Local Users and Groups → User (→ user limited)).
 - For details s. Bosch Security Knowledge Base <https://cp-vcsvideo.kb.net/al/12/2/article.aspx?aid=7400&tab=search&bt=4&r=>
- Default IP Address: The system comes with the following network settings
 - IP Address: 192.168.178.200
 - Subnet mask: 255.255.0.0



From	Product Management	Telephone	Nuremberg
ST-VS	ST-VS/MKP1	+49 911 93456 0	12-Jan-2015

- Initial installation: During initial boot and installation the system must be connected to the network. Please note: All systems come with the same default IP address.
- Network Settings Change: The DIVAR IP needs to be restarted, if network settings are changed in the Wizard. This applies for the initial setup as well as for changes during standard operation.
- Adding Storage: If the wizard stops at Step 8 “Add storage”, because the LUNs aren’t formatted, the LUNs have to be formatted using the Bosch VMS Config Client.
- ONVIF Support Restrictions
 - no support for event-based recording
 - Audio on some 3rd Party cameras not fully supported which may result in non-availability of audio streams
 - TCP not supported for ONVIF cameras but with UDP protocol only
 - Motion JPEG is not supported
 - VCA is always recorded for Bosch devices
 - VCA is not available for ONVIF cameras

New Features

The DIVAR IP 7000 Family is an all-in-one management solution that comes with BVMS/VRM including Video Streaming Gateway pre-installed and with 32 channels pre-licensed. The system will come with one built-in Transcoder channel.

Applied Changes / Bug Fixes

n/a