

D1265 Touch Screen Keypad

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Bright 480 by 272 TFT color graphic touch screen display provides excellent visibility
- ▶ Simple menu operation allows ease of use for novice users and familiarity for experts
- ▶ System instructions through Integrated on-screen Help
- ▶ Easy installation with self-locking base and chassis design including integrated bubble level
- ▶ Compatible with several intrusion control panels

The D1265 Touch Screen Keypad is an SDI bus compatible with several intrusion control panels by Bosch. Each keypad has an illuminated touch screen to display system messages and graphical buttons for data or command entry, and a sounder that emits eight warning tones.

Functions

Touch Screen Display

The D1265 keypad uses up to four rows of 20 characters each to display system messages and/or graphical buttons used to select a menu and associated functions. In addition to system messages and graphical buttons, the keypad displays, as needed, ten numeric buttons (0 to 9) and two function buttons (CMD and ENTER). Use the **COMMAND** button in combination with numeric buttons to perform a function. Use the **ENTER** button to enter your passcode.

When several events occur, the keypad shows each event in order of priority.

Audible Tones

The sounder emits eight distinct warning tones. You can adjust the volume. You can also use a passcode to silence the tone.

Certifications and approvals

The D1265 keypad is designed to comply with the requirements of:

USA	FCC	Part 15
EC Directives	RoHS	Directive 2002/95/EC Restriction of the use of certain Hazardous Substances
	WEEE	Directive 2002/96/EC Waste Electrical and Electronic Equipment

Installation/configuration notes

Compatible Control Panels

- B9512G/B9512G-E
- B8512G/B8512G-E
- D9412GV4/D7412GV4/D7212GV4¹
- D9412GV3/D7412GV3/D7212GV3¹
- D9412GV2/D7412GV2/D7212GV2¹ v7.04 and higher²

¹The D7212GV4, D7212GV3, and D7212GV2 are not listed for commercial fire applications

²D9412GV2/D7412GV2/D7212GV2 firmware prior to v7.04 and the D9412G/D7412G/D7212G control panels support the keypad but the LEDs do not light

Power Supplies

A compatible control panel supplies the power and data requirements to a D1265 keypad through a simple four-wire connection. To determine if an additional power supply is needed, use the operation and installation manual for the specific control panel and refer to the current rating chart for standby battery calculations.

Wiring Considerations

Use 1.2 mm (18 AWG) or 0.8 mm (22 AWG) wire. Each D1265 keypad includes a four position terminal strip located on the backplate for easy removal.

Parts included

Quant.	Component
1	Keypad
1	Literature <ul style="list-style-type: none"> • Quick Installation Guide • Literature CD

Technical specifications**Electrical Requirements**

Voltage:	12 VDC nominal
Wire Length	1000 ft of 18 awg
Standby Current:	Idle 135 mA Maximum 300 mA, with the sounder and display backlight at maximum

Environmental Requirements

Environment:	Indoor, dry
Relative Humidity:	90% at +50°C (+122°F)
Temperature (operating):	-10°C to +60°C (+14°F to +140°F)

Mechanical Properties

Color (enclosure):	White
Dimensions:	119 mm x 122 mm x 29 mm (4.7 in. x 4.8 in. x 1.2 in.)
Weight (Keypad):	0.24 kg (0.55 lb)

Ordering information**D1265 Touch Screen Keypad**

Illuminated touch screen keypad.

Order number **D1265**

Represented by:

North America:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

Latin America and Caribbean:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com