

# DS1108i Glassbreak Detector

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Microprocessor-based sound analysis technology (SAT)
- ▶ Automatic environmental test circuitry
- ▶ Sound check

The DS1108i Detector uses microprocessor-based sound analysis technology (SAT) to listen for the specific frequencies associated with breaking glass. The DS1108i can be used to detect breakage of plate, tempered, laminated and wired glass types. A built-in environmental test feature alerts the installer to false alarm hazards in harsh environments. The round enclosure mounts on ceilings or walls.

## Functions

### Signal Processing

Audio signals are analyzed using microprocessor-based SAT and must produce specific frequency, signature, and timing relationships to cause an alarm. The sophistication of this processing technique ensures proper catch performance while eliminating false alarms.

### Test Features

The magnet-operated test mode provides a location verification and operational test when using the optional DS1110i Glassbreak Tester. The test mode also includes an environmental test that alerts the installer to possible false alarm sources caused by ambient noise. The automatic sound check feature allows the end user to verify that the detector is

powered and functioning by clapping hands. An externally-visible alarm LED indicates an alarm or test condition and can be programmed to latch if desired.

## Certifications and approvals

Region	Certification	
Europe	CE	DS1101i
USA	UL	DS1108i: ANSR: Intrusion Detection Units (UL639) DS1108i

## Installation/configuration notes



### Notice

Glassbreak detectors are intended only as a component of a perimeter protection system. They should always be used in conjunction with motion sensors.

### Mounting

Mount the DS1108i detector on the ceiling, or on the wall opposite or adjacent to the window. Coverage depends on room acoustics and window size.

**Standard Coverage**

7.6 m (25 ft) for glass sizes over 30.5 cm x 30.5 cm (12 in. x 12 in.).

**Parts included**

Quantity	Component
1	Detector
1	Literature pack

**Technical specifications****Electrical**

Current:	21 mA nominal at 12 VDC
Voltage:	9 VDC to 15 VDC

**Environmental**

Operating Temperature:	-29°C to +49°C (-20°F to +120°F) <i>For UL Certificated installations, 0°C to +49°C (+32°F to +120°F)</i>
Radio Frequency Interference (RFI) Immunity:	No alarm or setup on critical frequencies in the range from 26 MHz to 950 MHz at 50 V/m.

**Mechanical**

Dimensions (HxDiameter):	2.1 cm x 8.6 cm (0.83 in. x 3.4 in.)
Material:	High-impact ABS plastic enclosure

**Outputs**

Alarm:	Normally-closed (NC) reed relay rated at 3.5 W, 125 mA at 28 VDC for resistive loads
Tamper:	Normally-closed (NC) cover-activated tamper switch with separate terminals. Contacts rated at 28 VDC, 125 mA maximum.

**Ordering information****DS1108i Glassbreak Detector**

Round detector uses microprocessor-based sound analysis technology (SAT) to listen for the specific frequencies associated with breaking glass.

Order number **DS1108i**

**Accessories****DS1110i Glassbreak Tester**

Used to test DS1101i, DS1102i, DS1103i, and DS1108i Glass Break Detectors.

Order number **DS1110i**

**Represented by:**

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
emea.securitysystems@bosch.com  
emea.boschsecurity.com

**Germany:**  
Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Ring 5  
85630 Grasbrunn  
Germany  
www.boschsecurity.com

**North America:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
onlinehelp@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia