# **Learn Mode Slim Line Door and Window Se** nsors

www.boschsecurity.com





- ▶ Flat design
- ▶ Fits in most small areas
- Replaceable battery

The Learn Mode Slim Line Door and Window Sensors include a white model and a brown model. Each model is narrow and suitable to use on doors, windows, jewelry cases, gun cabinets and anything that opens and closes.

## **Functions**

### **Learn Mode Technology**

Each device has a unique, programmed identity. Control panels recognize and learn the identity of each device in the system, eliminating programming errors in the field.

# Installation/configuration notes

# **Compatibility Information**

Receivers: RF3226 Quik Bridge Receiver

Quik Bridge Learn Mode Loop Receiver

(P/N: 60-660-01-95R)

**Expanders** D208RF Receiver Expander

D216RF Receiver Expander

## Mounting

Mount the magnet on a door or window and the sensor on the frame.

# **Parts included**

Quantit y	Component
1	Sensor housing
1	Magnet housing
1	Adhesive pad
1	Tamper spring
1	Hardware pack
1	Literature pack

# **Technical specifications**

#### **Electrical**

Battery:	3.6 VDC (½ AA) lithium battery (P/N: 34-026)
Battery Life:	5 to 8 years

#### Mechanical

Color:	60-499-10-319.5: White
	60-499-11-319.5: Brown
Dimensions:	0.31 in. x 4.94 in. x 0.88 in. (0.8 cm x 11.2 cm x 2.0 cm)
Weight:	51 g (1.8 oz)
Radio Frequency:	319.5 MHz
Bandwidth:	24 kHz

## **Environmental**

(+10°F to +120°F)	Temperature Range:	-12°C to +49°C (+10°F to +120°F)
-------------------	--------------------	-------------------------------------

# **Ordering information**

#### Slim Line Door and Window Sensor (White)

Slim Line Door and Window Sensor; white model Order number **60-499-10-3195** 

## Slim Line Door and Window Sensor (Brown)

Slim Line Door and Window Sensor; brown model Order number 60-499-11-3195

#### **Accessories**

## Extra Magnet (Brown)

For door, window, and shock magnets Order number **60-555-11** 

#### **Extra Magnet (White)**

For door, window, and shock magnets Order number **60-555-10** 

# **Radio Frequency Sniffer**

Emits a series of beeps when RF transmission is detected

Order number 60-401

# Slim Line Door Case (Brown)

Used to replace damaged or blemished cases Order number **80-089-11** 

## Slim Line Door Case (White)

Used to replace damaged or blemished cases Order number **80-089-10** 

## Represented by:

Americas: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 security.sales@us.bosch.com www.boschsecurity.us Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

#### China:

Bosch (Shanghai) Security Systems Ltd. 201 Building, No. 333 Fuquan Road North IBP Changning District, Shanghai 200335 China Phone 486 21 22181111 Fax: +86 21 2218398 www.boschsecurity.com.cn

#### America Latina:

Robert Bosch Ltda Security Systems Division Via Anhanguera, Km 98 CEP 13065-900 Campinas, Sao Paulo, Brazil Phone: +55 19 2103 2860 Fax: +55 19 2103 2862 latam.boschsecurity@bosch.com www.boschsecurity.com